



- c. What does this prompt mean?
- 

## Step 2 Login to the router in privileged EXEC mode

- a. Enter **enable** at the user mode prompt.  
Router>**enable**
- b. If prompted for a password, enter the password class.
- c. What prompt did the router display?
- 

- d. What does this prompt mean?
- 

## Step 3 Enter global configuration mode

- a. Enter **configure terminal** at the privilege mode prompt.  
Router#**configure terminal**
- b. What prompt did the router display? \_\_\_\_\_
- c. What does this prompt mean?
- 

## Step 4 Enter router configuration mode

- a. Enter **router rip** at the global configuration mode.  
Router(config)#**router rip**
- b. What prompt did the router display? \_\_\_\_\_
- c. What does this prompt mean?
- 

## Step 5 Exit from router mode and go into interface configuration mode

- a. Enter **exit** at the prompt to return to global configuration mode.  
Router(config-router)#**exit**
- b. Enter **interface serial 0** at the global configuration mode prompt.  
**Note:** See chart for the interface identifier.  
Router(config)#**interface serial 0**
- c. What prompt did the router display? \_\_\_\_\_
- d. What does this prompt mean?
- 

- e. Enter **exit** at the prompt to return to global configuration mode.  
Router(config-if)#**exit**

### Step 6 Assign a name to the router

- a. Router (config) #**hostname GAD**
- b. What prompt did the router display? \_\_\_\_\_
- c. What does this prompt mean?

---

d. What change has occurred in the prompt?

---

### Step 7 Exit the router

- a. Enter **exit** at the prompt to close out of the router.  
GAD (config) #**exit**
- b. From the privileged EXEC mode, type exit to logoff. Turn the router off.

## Erasing and reloading the router

Enter into the privileged EXEC mode by typing **enable**.

If prompted for a password, enter **class**. If “class” does not work, ask the instructor for assistance.

```
Router>enable
```

At the privileged EXEC mode, enter the command **erase startup-config**.

```
Router#erase startup-config
```

The responding line prompt will be:

```
Erasing the nvram filesystem will remove all files! Continue?  
[confirm]
```

Press **Enter** to confirm.

The response should be:

```
Erase of nvram: complete
```

Now at the privileged EXEC mode, enter the command **reload**.

```
Router#reload
```

The responding line prompt will be:

```
System configuration has been modified. Save? [yes/no]:
```

Type **n** and then press **Enter**.

The responding line prompt will be:

```
Proceed with reload? [confirm]
```

Press **Enter** to confirm.

In the first line of the response will be:

```
Reload requested by console.
```

After the router has reloaded the line prompt will be:

```
Would you like to enter the initial configuration dialog? [yes/no]:
```

Type **n** and then press **Enter**.

The responding line prompt will be:

```
Press RETURN to get started!
```

Press **Enter**.

The router is ready for the assigned lab to be performed.

<b>Router Interface Summary</b>					
Router Model	Ethernet Interface #1	Ethernet Interface #2	Serial Interface #1	Serial Interface #2	Interface #5
800 (806)	Ethernet 0 (E0)	Ethernet 1 (E1)			
1600	Ethernet 0 (E0)	Ethernet 1 (E1)	Serial 0 (S0)	Serial 1 (S1)	
1700	FastEthernet 0 (FA0)	FastEthernet 1 (FA1)	Serial 0 (S0)	Serial 1 (S1)	
2500	Ethernet 0 (E0)	Ethernet 1 (E1)	Serial 0 (S0)	Serial 1 (S1)	
2600	FastEthernet 0/0 (FA0/0)	FastEthernet 0/1 (FA0/1)	Serial 0/0 (S0/0)	Serial 0/1 (S0/1)	
<p>In order to find out exactly how the router is configured, look at the interfaces. This will identify the type of router as well as how many interfaces the router has. There is no way to effectively list all of the combinations of configurations for each router class. What is provided are the identifiers for the possible combinations of interfaces in the device. This interface chart does not include any other type of interface even though a specific router may contain one. An example of this might be an ISDN BRI interface. The string in parenthesis is the legal abbreviation that can be used in IOS command to represent the interface.</p>					